

WLAN konfiguration, 2702

AP standalone

```
dot11 ssid wikilander
  vlan 1337
  authentication open
  authentication key-management wpa version 2
  mbssid guest-mode
  wpa-psk ascii LÖSENORD
```

```
interface Dot11Radio0
  encryption vlan 1337 mode ciphers aes-ccm
  ssid wikilander
```

```
interface Dot11Radio0.1337
  encapsulation dot1Q 1337
  bridge-group 12
  bridge-group 12 subscriber-loop-control
  bridge-group 12 spanning-disabled
  bridge-group 12 block-unknown-source
  no bridge-group 12 source-learning
  no bridge-group 12 unicast-flooding
```

```
interface Dot11Radio1
  encryption vlan 1337 mode ciphers aes-ccm
  ssid wikilander
```

```
interface Dot11Radio1.1337
  encapsulation dot1Q 1337
  bridge-group 12
  bridge-group 12 subscriber-loop-control
  bridge-group 12 spanning-disabled
  bridge-group 12 block-unknown-source
  no bridge-group 12 source-learning
  no bridge-group 12 unicast-flooding
```

```
interface GigabitEthernet0.1337
 encapsulation dot1Q 1337
 bridge-group 12
 bridge-group 12 spanning-disabled
 no bridge-group 12 source-learning
```

Vill man ändra vilken wifikanal som används gör man det under Dot11Radio-interfacen med kommandot `channel <kanal>`.

Revision #2

Created 26 April 2025 11:49:22 by Jehrlander

Updated 14 August 2025 19:14:50 by Jehrlander